

JARVIS PAS TESTER

Model AST 106



Not for use with Jarvis Models USSS-1, USSS-21, 2, 2A and USSS-1/2 Pneumatic Stunners.

The Jarvis Model AST 106 Tester - for Jarvis stunners PAS Type C and Type P bolt speed measurements.

JARVIS®

- Fast, accurate testing of Jarvis power load stunners.
- Easy to use - intuitive operation.
- Data log for test audits.
- Complies with most stringent requirements or audit data collections.



FAST - RELIABLE - ACCURATE

JARVIS PAS TESTER

Model AST 106

Specifications

Model AST-106

Power Requirements	115 V / 0.3 A or 220 V / 0.2 A	
Operating Voltage	115 V, 1 phase, 60 Hz 230 V, 1 phase, 50 / 60 Hz	
Overall Dimensions		
Test Stand (Ø x height)	7 in x 10 in	178 mm x 254 mm
Control Box (length x height x width)	12 x 10 x 4 in	305 x 254 x 102 mm
Weight		
Test Stand	23 lbs	10.4 kg
Control Box	5 lbs	2.3 kg

Equipment Selection and Accessories

Order Number

Model AST 106 Jarvis PAS Tester (includes test stand and control box)		
	115 V, 60 Hz	4116001
	230 V, 50 / 60 Hz	4116002
Test Stand		3161610
Control Box	110 - 240 V, 1 phase, 50 / 60 Hz	3163001
*Does not include electric power cord		
Electric Power Cord	9 ft / 115 V (assy)	3001008
	6 ft / 230 V (cord only)	1101002

JARVIS®

Products for the meat and poultry industry

Jarvis Products Corporation · 33 Anderson Road · Middletown, CT 06457-4926 · United States of America
Telephone (860) 347-7271 · Fax (860) 347-9905 · president4@hotmail.com · www.jarvisproducts.com